

THE PINSKE EDGE

#242500 POWER STANDS

Pinske Power Stands are sturdy, compact and portable – fast and simple to set up and take down. These stands can be used with 48”, 96” or 144” Rails and are easy to rearrange for each new project. You can place your sheets on the workstation and leave them there from rough cut through final seam. The less you move your pieces, the less chance there is of chipped edges or other damage.

To set up your stands, simply unfold them and connect the cross arms to the lower pins. Place the hairpin through the hole to secure the arm.

Assembly of the Cam Clamp is necessary before installing Rails onto the Power Stands - See detailed drawing specs.

1. Place the 5/16 x 2 ½” Bolt with 5/16” Flat Washer from the outside through the hole in the upper part of the Power Stand.
2. On the other side of the tube, slide the #012759 ¾” Spring onto the Bolt.
3. Place the #012758 Steel Cam Lock Bar onto the Bolt.
4. Then place the #012757 Plastic Washer onto the Bolt.
5. Take the #012750 Cam Clamp and thread the Bolt into the Cam Clamp.
6. Perform this on each side of Power Stands.
7. The Rail should be placed on the inside of the Stand (with the Rail resting on top of the Stand leg).
8. Press the Cam Clamp down to tighten it. There will be substantial resistance in order to securely hold the Rail in place. (If you don't feel that it is tight enough, flip the Cam Clamp back up and tighten the bolt.)

We recommend setting up your stands about 20”- 24” in from the end of your 144” or 96” Rails – this gives you more support and keeps the rails nice and straight with the weight of your project.

You may even add additional flexibility to your Power Stands with our Move-Eze Wheels. Use one set of Move-Eze Wheels for each pair of Power Stands. These would simply attach to the bottom brace on each stand, making the stands easy to move around your shop.

The Pinske Edge
119 Main Street, P.O. Box 68
Plato, MN 55370 USA
Fax – 320-238-2385 - Phone 320-238-2196 or 1-800-TPINSKE
www.pinske-edge.com – info@pinske-edge.com